

POWERTECH PLUS



0-36VDC 0-5A Slimline 80W
Lab Power Supply
MP-3842
User Manual

FUNCTION

This product has a high-precision output and low ripple AC / DC power. It can provide a DC output voltage within the range of 0-36V.

It's designed to provide continuous power output of 80W Max, It can be used for electronic products in laboratories, factories and even at home as a high-precision power supply.

SPECIFICATIONS

INPUT:

Input Voltage: 100-240V AC 60/50 Hz
Input Current: 1100mA
Fuse: 250V 2A
Input line: 0.75mm² 1.8m

OUTPUT:

Voltage 1: 0-16V/DC 0-5A (max)
Voltage 2: 0-27V/DC 0-3A (max)
Voltage 3: 0-36V/DC 0-2.2A (max)
Output Power: 80(MAX)

Operation temperature: 0° - 40°
Store temperature: -20° - 60°
Size: 53(W) x 300(L) x 138(H)mm
Weight: 866g

PANEL

1. The digital voltmeter
2. Digital ammeter
3. "CV" Output Mode
4. "CC" Output Mode
5. Voltage adjusting knob
6. Current adjustment knob
7. Output select button
8. Output ON / OFF
9. DC output negative
10. DC output positive
11. AC Mains power switch
12. AC Mains inlet



INSTRUCTIONS

1. Before using the device, check if the AC input voltage is within 100-240V AC range.
2. Turn ON the AC Mains power switch.
3. Select the Output:
 - Maximum output voltage of 16V, maximum current 5A
 - Maximum output voltage of 27V, maximum current 3A
 - Maximum output voltage of 36V, maximum current 2.2A
4. To adjust voltage:
 - Press Output ON button. Adjust the voltage using the voltage adjustment knob.
 - Turn Output OFF.
5. To adjust the current:
 - Using the red and black output leads, short the '+' and '-'
 - Press Output ON button. Adjust the current using the current adjustment knob.
 - Turn Output OFF and remove short. The current limit is set.
6. To start using, press the Output ON button.
7. Turn OFF the Output and turn OFF the AC Mains power switch after using device.

WARNING

1. Do not place objects on the device.
2. The product is for indoor use only. Do not expose to sun or rain.
3. Ensure proper ventilation when using the device.
4. Ensure the device is mounted properly on an even surface.
5. When replacing the fuse, use the same type/size fuse.
6. When replacing the AC Mains input cable, ensure wires are equal to or greater than 0.75 mm².
7. The device has short circuit and overcurrent protection.
8. Do not overload the device above the rated voltage and current. This will trigger the overcurrent /short circuit protection.
9. Do not attempt to repair the device.

SAFETY TIPS

1. Do not disassemble.
2. Avoid exposure to excessive heat (over 60 degrees Celsius).
3. Do not expose to wet or corrosive environments.
4. Do not short the output.
5. Do not put pressure on the device.
6. This product is not a toy. Keep out of reach of children.

Distributed by:
TechBrands by Electus Distribution Pty. Ltd.
320 Victoria Rd, Rydalmere NSW 2116 Australia
Ph: 1300 738 555
Int'l: +61 2 8832 3200
Fax: 1300 738 500
www.techbrands.com

Made in China